

HOW TO CORNER YOURSELF WITH GREAT SOUND


Introduction to Cornered Ci2

CORNERED AUDIO®

Contents of the manual are subject to change without notice. CORNERED Audio does not accept any liability for loss or damage caused or alleged to be caused directly or indirectly by these instructions. CORNERED Audio makes no guarantee of any kind with regard to these instructions.

Introduction

Congratulations on your purchase of the CORNERED Ci loudspeaker system. The Ci series is a feature packed range of loudspeakers designed for use in a large variety of applications. Emphasis is placed on discreet modern design, ease of installation, wide and uniform coverage and excellent sound quality without the use of electronic signal processing.



Included in the box

Two speakers:
Mounting screws
Mounting template
Manual

The triangular cabinet allows for discreet installation in corners or on walls and ceilings. Cabinets can be coupled together to expand coverage and installation is fast and simple with the integrated mounting points. Please read the manual to ensure best possible performance from your CORNERED loudspeaker.


Please read the manual to ensure best possible performance from your CORNERED loudspeaker.

Getting started



How to connect the cables

The Ci models are fitted with spring loaded terminals on the front baffle. Contacts will accept up to 2,0 sq. mm wire with an outside diameter of up to 10mm.

* Note: It is important that you run the speaker cables through the port BEFORE installing your new CORNERED speakers! The speakers are equipped with discreet cable terminals placed on the front baffle behind the front cover - and it is not possible to run the cables to the terminals once the speakers have been installed.



- 1 Remove the front cover to access the cable terminal: Push the cover from the side of the cabinet to squeeze it out of the groove.
- 2 Make sure the amplifier is turned off.



- 3 Run the speaker cable through the tube positioned at the rear of the cabinet to the terminal at the front baffle.
- 4 Connect the cable to the terminal after the speaker is mounted to the wall.


* Note that it is easier to install the speaker first and mount the cable to the terminal after the speaker is mounted to the wall.

Installation

The Ci series can be mounted either in corners or on walls and ceilings with the integrated mounting points. They can also be coupled together to extend coverage. The Ci2 is very light, but please make sure that the wall or ceiling is solid and can support the weight of the speaker before installing. Also, make sure that you comply with all local health and safety regulations. The low weight allow the products to be installed easily by one person.

Vertical or horizontal installation in corners

If you prefer to mount the speaker in a corner, you should:




- 1 Remove the front cover and you'll see the mounting holes on the front of the cabinet.

- 2 Place the mounting template in desired position and mark drilling positions by shading through the two mounting holes

- Drill holes in the wall using 4mm raw plugs and the enclosed 3,5 mm flat head screws.
- Reposition the speakers in desired position and mount the screws.

Mounting in corners that are not exactly 90 degrees:

- If the corner is less than 90 degrees, simply place the speaker cabinet as deep in the corner as possible and use all mounting points. This will leave a little space behind the cabinet and the walls, but the speakers will still appear with a nice finish in the corner.
- If the corner is more than 90 degrees, we recommend mounting only one of the sides of the speaker cabinet onto the wall - and leave some air behind the other side of the cabinet. This will not be visible from the front, and the speakers will still present themselves with a nice finish.



When you have installed the speaker to the wall or ceiling, then connect the speaker cable to the terminal and reinstall the front cover.


Connect the red (+) speaker cable to the red cable terminal and the black (-) speaker cable to the black speaker terminal.

Mounting the cabinets together

CORNERED speakers are designed with emphasis on uniform and wide controlled dispersion. The acoustic design allows the speakers to be coupled together to expand coverage:

- One Ci cabinet offers 100x100 degree dispersion.
- Two Ci cabinets can be coupled together back to back and then mounted flush onto walls and ceilings while offering 200 degrees of coverage with minimum phase cancellation.

If you wish to mount the speakers together, simply mount the speakers back to back on wall or ceiling using the integrated mounting points as shown below:



Two Ci2's mounted back to back.

Cables

Speaker cables present the amplifier with different loads. Cables with high capacitance, high inductance and high impedance have a strong negative influence on sound quality as well as amplifier reliability. In order to get the most out of the speaker system, avoid using thin speaker cables.

We recommend the CORNERED CSP2 speaker cable designed to fit in corners or flush on walls.

The thickness of the cable relates to the length of the cable. For very long cable runs, 4 sq mm. cables should be used. When running the cable through the tube, simply remove the outer isolation material from the cable and run the separate wires to the speaker terminals.

To minimize power loss and response variations, please refer to the following table for guidance, showing the maximum recommended cable length relative to impedance and cable thickness:

Cable size/load	8 ohm	4 ohm	2 ohm
2 sq mm.	20m/65ft.	10m/32ft.	5m/16ft.
2,5 sq mm.	30m/100ft.	15m/50ft.	7,5m/25ft.
4 sq mm.	60m/200ft.	30m/100ft.	15m/50ft.

Outdoor mounting

The Ci series is IP64 rated, so they can be placed outside. If installed outdoors, the insulation of the cabling should be resistant to water as well as the effects of temperature and ultraviolet radiation from the sun. Recommended insulations are: UV stabilized polyethylene, neoprene, Teflon™, Silicon™, and Hypalon™. The following materials are not recommended, because of potentially shorter life expectancy in outdoor environments: rubber, PVC (polyvinylchloride), polypropylene, polyurethane, and nylon. UV-stabilized polypropylene may be acceptable.

Safety wire

In installation terms, the CORNERED top-boxes are as much brackets as they are speakers, because they mount flush to the walls and ceilings, so no safety wire is needed (just like on traditional speaker installations, you don't use a safety wire from a bracket to the wall).

Operation

Recommended amplifier

CORNERED speakers have high minimum impedance, making them an easy load for amplifiers. Typical pro amplifiers will run three speakers per channel without problems. We recommend amplifiers with a minimum output on level with the highest recommended amplifier output in the specifications.

As with all loudspeaker systems, power handling depends on the quality and size of the amplifier. If overdriving the amplifier and running it into clipping, the drive units can be damaged even if the amplifier output is lower than the power handling of the speaker.


When choosing an amplifier, note that generally a higher power amplifier running free of distortion will sound better and do less damage to the loudspeaker than a lower power amplifier continually clipping. See technical specifications section for recommended amplifier power.

Break-in time

As with all quality loudspeakers, your Ci2 has to play for app. 30 hours before performing to specification.

Service

Woofers can be easily replaced by unscrewing them from the baffle using a Hexagon H3 bit. The tweeter is clicked into the horn section of the baffle from the rear of the baffle. To access the tweeter, remove the baffle by unscrewing the four Philips screws.



Turn the tweeter counter-clockwise to remove it from the baffle. Reinstall the new tweeter by pressing it towards the horn section of the baffle and turn it clock wise until you hear a "click".

Specifications

Ci2

Power handling, IEC268:	30 watt
Power handling, peak:	120 watt
Sensitivity, 2,83V/1m:	84 dB
Maximum SPL, long term:	99 dB
Maximum SPL, peak:	105 dB
Frequency response:	140-20.000 Hz
Nominal impedance:	8 ohm
Dispersion:	100x100 degrees
Measurements:	(HxWxD) 181x135x102mm
Weight:	0,75 kg
Colour:	Black - White

Ci4

Power handling, IEC268:	60 watt
Power handling, peak:	240 watt
Sensitivity, 2,83V/1m:	86 dB
Maximum SPL, long term:	104 dB
Maximum SPL, peak:	110 dB
Frequency response:	60-20.000 Hz
Nominal impedance:	8 ohm
Dispersion:	100x100 degree
Measurements:	(HxWxD) 400x190x145mm
Weight:	2,4 kg (Ci4 - 2,35 kg)
Colour:	Black - White

Ci4-V high impedance data: Selectable taps at 7,5W or 15W @ 100V or 3,75W, 7,5W or 15W @ 70V

Ci5

Power handling, IEC268:	80 watt
Power handling, Peak:	320 watt
Sensitivity, 2,83V/1m:	88 dB
Maximum SPL: Long term:	107 dB
Maximum SPL: Peak:	113 dB
Frequency response:	55-20.000 Hz
Nominal impedance:	8 ohm
Dispersion:	100x100 degree
Measurements:	(HxWxD) 450x209x150mm
Weight:	3,6 kg (Ci5 - 3,55 kg)

Ci5-V high impedance data: Selectable taps at 7,5W, 15W or 30W @ 100V or 70V

Declaration of conformity

Manufacturer:

CORNERED Audio ApS
Rosenkæret 13 2.tv
Denmark

We, CORNERED Audio ApS, declare under our responsibility that the following product(s):

CI2
Type: Loudspeaker

...are in conformity with: COUNCIL DIRECTIVE of 3 May 1989 on the approximation of the laws of the Member States relating to electromagnetic compatibility (89/336/EEC) ..and has been manufactured in conformity with the following national standards that implements a harmonized standard:

EN 55013

Limits and methods of measurement of radio disturbance characteristics of broadcast receivers and associated equipment.



Hans V. Madsen / Founder & CEO
18.07.2017